THE UNIVERSITY *of* EDINBURGH

Edinburgh Research Explorer

10 Mb/s visible light transmission system using a polymer light-emitting diode with orthogonal frequency division multiplexing

Citation for published version:

Le, ST, Kanesan, T, Bausi, F, Haigh, PA, Rajbhandari, S, Ghassemlooy, Z, Papakonstantinou, I, Popoola, WO, Burton, A, Le Minh, H, Cacialli, F & Ellis, AD 2014, '10 Mb/s visible light transmission system using a polymer light-emitting diode with orthogonal frequency division multiplexing', *Optics Letters*, vol. 39, no. 13, pp. 3876-3879. <https://doi.org/10.1364/OL.39.003876>

Digital Object Identifier (DOI):

[10.1364/OL.39.003876](https://doi.org/10.1364/OL.39.003876)

Link:

[Link to publication record in Edinburgh Research Explorer](#)

Document Version:

Peer reviewed version

Published In:

Optics Letters

General rights

Copyright for the publications made accessible via the Edinburgh Research Explorer is retained by the author(s) and / or other copyright owners and it is a condition of accessing these publications that users recognise and abide by the legal requirements associated with these rights.

Take down policy

The University of Edinburgh has made every reasonable effort to ensure that Edinburgh Research Explorer content complies with UK legislation. If you believe that the public display of this file breaches copyright please contact openaccess@ed.ac.uk providing details, and we will remove access to the work immediately and investigate your claim.

A 10 Mb/s Visible Light Transmission System using a Polymer Light-Emitting Diode with Orthogonal Frequency Division Multiplexing

Son T. Le,¹ T. Kanesan,¹ F. Bausi,^{5,6} P. A. Haigh,^{2,3} S. Rajbhandari,⁴ Z. Ghassemlooy,² I. Papakonstantinou,^{3,6} W. O. Popoola,⁷ A. Burton,² H. Le Minh,² F. Cacialli^{5,6} and A. D. Ellis¹

¹ Aston Institute of Photonic Technologies, Aston University, Birmingham, B4 7ET, UK

² Optical Communications Research Group, Northumbria University, Newcastle-upon-Tyne, NE1 8ST, UK

³ Department of Electronic and Electrical Engineering, University College London, WC1E 6BT, UK

⁴ Department of Engineering Science, University of Oxford, Parks Road, Oxford, OX1 3PJ, UK

⁵ Department of Physics and Astronomy, University College London, WC1E 6BT, UK

⁶ London Centre for Nanotechnology, University College London, WC1E 6BT, UK

⁷ School of Engineering and Built Environment, Glasgow Caledonian University, Glasgow, G4 0BA, UK

*Corresponding author: let1@aston.ac.uk, paul.haigh@northumbria.ac.uk, f.bausi@ucl.ac.uk

Received Month X, XXXX; revised Month X, XXXX; accepted Month X, XXXX; posted Month X, XXXX (Doc. ID XXXXX); published Month X, XXXX

We present a new designed polymer light emitting diode with a bandwidth of ~350 kHz for high-speed visible light communications. Using this new polymer light emitting diode as a transmitter, we have achieved a record transmission speed of 10 Mb/s for a polymer light emitting diode based optical communication system with orthogonal frequency division multiplexing technique, matching the performance of single carrier formats using multi-tap equalization. For achieving such a high data-rate, a power pre-emphasis technique was adopted. © 2014 Optical Society of America
OCIS Codes: (060.4510) Optical Communication; (250.3680) Light-emitting polymers

With the exponentially increasing demand for data caused by the limited (and therefore expensive) radio frequency (RF) bandwidth available, researchers are increasingly turning to optical domain technologies such as visible light communications (VLC). Currently, VLC is undergoing intense research to provide high capacity ubiquitous networks in future smart homes/offices by leveraging on the lighting infrastructure.

The optical transmitters in VLC links are generally accepted as phosphor-converted gallium nitride (GaN) light emitting diodes (LEDs) due to their high optical power and simplicity of implementation. Thus, the vast majority of experimental research reported in the field has utilized just a “solitary” LED to achieve high throughputs [1-3]. GaN LEDs are produced using epitaxial methods that result in brittle crystals; as such it is not trivial to produce devices with large photoactive areas. To provide illumination in a home/office environment would therefore require a matrix of LEDs, which has its own associated problems such as resonance in the circuitry and increasing system complexity. A far simpler approach would be to use a single panel with a large photoactive area.

As an alternative to inorganic LEDs, we consider here organic, polymeric LEDs (PLEDs) as the transmitter. Organic electronics is a technology that allows solution-based fabrication of semiconductor devices to concurrently have the properties of plastics (i.e. mechanical flexibility, and arbitrary shape) and the conduction properties of metals, as well as band gap tuning by selection of polymer to control the emission wavelength. These advantages are very important for VLC systems especially considering that large panel illumination devices can be produced with unrestricted shapes and sizes.

However, the major challenge when adopting PLEDs for VLC systems is the relatively small raw bandwidth. The

polymers used as semiconductors in PLEDs are characterized by the charge transport mobilities that are orders of magnitude lower than those available in crystalline inorganic semiconductors. In turn this causes a restricted PLED bandwidth that is also orders of magnitude lower than that obtainable from inorganic LEDs. As a result, achieving high capacity data communications with PLED is a substantial challenge that needs addressing.

Several reports of high throughput polymer VLC (PVLC) links are available in the literature. In [4] a 10 Mb/s link is experimentally demonstrated using the on-off-keying (OOK) modulation format and a 270 kHz bandwidth PLED in real time with an FPGA. This transmission data rate was achieved using a least mean squares equalizer with 25 tapped weight coefficients. In [5] a transmission speed of 2.7 Mb/s was reported for a system that only utilized ~90 kHz of bandwidth with an artificial neural network equalizer. However, these digital signal processing (DSP) based equalization techniques are highly computationally complex. Therefore, in order to bring PVLC systems closer to real-world applications, more DSP-efficient modulation formats and transmission schemes should be considered and explored.

It has been demonstrated that discrete multi-tone modulation schemes such as orthogonal frequency division multiplexing (OFDM) considerably outperform unequalized time domain modulation schemes such as OOK in VLC systems due to their high spectral efficiency, meaning that multiple bits per symbol can be transmitted to achieve a much higher bit rate [6]. In addition, OFDM is extremely robust against frequency-selective and multipath fading channels, resulting in an inherent protection against inter-symbol interference (ISI), thus, making OFDM the dominant modulation format in current

RF wireless communications. As a result, OFDM has been considered as a strong candidate for future VLC applications due to its inherent resilience to ISI [3, 7]. However, there is a lack of reported research on the performance of OFDM in PVLC-based systems. To the best of our knowledge, the only demonstration of an organic VLC link with OFDM was reported in [8], at a bit-rate of 1.4 Mb/s using a bandwidth of 93 kHz.

In this work, we present a 10 Mb/s PVLC link using custom designed PLEDs with an increased device bandwidth of ~ 350 kHz, which is a noteworthy improvement of around four times over [8]. The increase in bandwidth is achieved by using thermal annealing during the PLED manufacturing process. This results in a lower turn-on voltage and higher currents for a certain voltage, compared to our previous reports. The thermal annealing is expected to facilitate packing of the different polymer chains and therefore favor higher charge mobilities. By using such a PLED with OFDM as the transmission scheme and a power pre-emphasis technique, we have successfully transmitted a 10 Mb/s data stream without using any complex multi-tap equalization schemes. In comparison with the previous PVLC OFDM transmission systems [8], this represents significant improvements both in the achievable data rate (10Mb/s in comparison to 1.4Mb/s) and also in the net data-rate/bandwidth gain (30 times here in comparison to 14 times in [8]). For the purpose of comparison, we also present here the performance of an unequalized OOK system using the same PLED.

One of the main limits of organic based photonic devices is the degradation mechanisms of the polymers due to contact with oxygen/water from air, which drastically limits performance and lifetime. For this reason, PLEDs are usually prepared under nitrogen atmosphere. In this work, encapsulated PLEDs were prepared that allowed safe utilization in air without any apparent degradation with time. A schematic and photograph of the PLED used in this work is shown in Fig. 1.

For the preparation of the devices, a glass substrate is used with pre-patterned indium tin oxide (ITO) as a transparent anode (Ossila Ltd). The ITO was cleaned with sonication in acetone and isopropanol and treated with oxygen plasma [9] to increase the work function and reduce the surface roughness. Immediately following this we spin-coated (5000 rpm for 30 s in air) a water dispersion of PEDOT:PSS (Heraeus Clevios™ P VP AI 4083) to produce a hole-injection layer of approximately 40 nm thickness. The polymeric layer was annealed at 180°C for 600 s in nitrogen atmosphere to remove any water residue. Then the active layer of poly [2-methoxy-5-(3',7'-dimethyloctyloxy)-1,4-phenylenevinylene] (MDMO-PPV) with a Mn of $\sim 23,000$ g/mol (Sigma-Aldrich) was deposited via spin coating (2,000 rpm for 60 s) from a 1% w/w (8.76 g/mL) solution in toluene. We then annealed the samples for 10 minutes at 150° C, i.e. above the glass transition temperature. The annealing is expected to induce a reorganization of the polymer chains, thus favoring the inter-chain interaction and hence determining a better charge transport [10], resulting in a higher bandwidth compared to the previous work [4] while causing a partial but acceptable decrease in the luminance from 17,000 to cd/m^2 to 12,000 cd/m^2 at 10 mA operation

(Fig. 2).

Fig. 1. An exploded schematic of the PLED used in this work; inset is a top view photograph of a single 3.5 mm² photoactive area PLED at 8 V (DC bias). To prevent air exposure of the cathode and the polymer layers the device is covered with a film of epoxy glue and a glass slide. The glass cover is smaller than the glass substrate to leave enough space to attach the pins. The external contact is made through an ITO stripe (left in the image above).

Fig. 2. The L-I-V curve of the PLED under test, shown in dashed lines are the plots for diodes used in [4]

Fig. 3. The frequency response curve of the PLED under test, the dashed line in red is the linear curve fitting

The ~ 30 nm metallic calcium cathode is evaporated in high vacuum, followed by evaporation of a ~ 150 nm protective aluminum layer. The devices were then encapsulated using epoxy glue (Ossila Ltd) to apply a protective glass slide on top of the layers. The glue was cured with the UV light ($4\text{--}5 \text{ mW/cm}^2$) for 15 minutes in nitrogen atmosphere to form a solid thin film that protects the device from the infiltration of oxygen and water. Contact legs were applied to the devices (Ossila Ltd). The

L-I-V curves, shown in Fig. 2, were measured for the PLED under test between 0 to 10 mA (solid lines) in comparison to [4] (dashed lines). As shown in Fig. 1, the metallic calcium cathode is connected to the contact pin through an ITO stripe to prevent air exposure. This ITO contact forms a resistance of about 100 Ω in series to the diode and this explains why, for any voltage, the current is lower in the encapsulated devices compared to the non-encapsulated one [4]. However, even with a higher series resistance, the encapsulated devices show a wider bandwidth than the non-encapsulated devices because the degradation due to air exposure is prevented. This suggests that an even higher bandwidth could be reached through a better design of encapsulated devices so as to achieve a lower series resistance. The PLEDs electroluminescence spectra feature a 600 nm peak with a similar emission profile as in [4]. The frequency response curve of the PLED under test is shown in Fig. 3.

Fig. 4. The schematic block diagram for the system under test, S/P: serial/parallel conversion, P/S: parallel/serial conversion, TS: training symbol, and VSG: vector signal generator

cyclic prefix was not required. It should be noted that the experiment was performed using a 3.5 mm² photoactive area pixel and hence the distance could be increased by increasing the photoactive area. Furthermore, the devices were encapsulated allowing transmission outside of a pumped vacuum environment for the first time. The received signal is sampled and digitized by a Tektronix MDO4104B-6 oscilloscope (1 GHz bandwidth). 10⁷ samples per acquisition were recorded with a sampling frequency that was varied according to the data rate to give a maximum of 10 Sa/sym. The data is then captured in MATLAB for further off-line processing with a standard OFDM receiver, including resampling, synchronization, single-tap equalization and symbol de-mapping.

$$[P(k)]_{dB} = \frac{3}{B} \cdot f_k$$

Fig. 5. Frequency spectra of the received OFDM signals (both with 1 MHz bandwidth) without (a) and with (b) power pre-emphasis

Fig. 6. Received constellation diagrams at 4.5 Mb/s without power pre-emphasis, before (a) and after (b) single-tap equalization

Fig. 7. The BER versus transmission data-rate for OFDM systems with and without power pre-emphasis and OOK.

The received constellation diagrams at 4.5 Mb/s without power pre-emphasis before and after single-tap equalization are shown in Fig. 6 (a) and (b), respectively. It is clear that the PLED and the system front end not only introduce amplitude distortion (acting a low-pass filter) but also phase distortion (introducing a frequency-dependent positive phase shift). As a result, with the increase of sub-carrier index (frequency), these amplitude and phase distortion perturbations rescale and rotate the received constellation points simultaneously. However, both the amplitude and phase distortions introduced by the PLED are frequency-dependent, and thus can be effectively corrected by transmitting a known symbol and performing single-tap equalization with the zero-forcing method. At a bit-rate of 4.5 Mb/s the data can be recovered with a bit error rate (BER) of $\sim 5.6 \times 10^{-3}$.

The BER performance of the investigated OFDM system with and without power pre-emphasis and unequalized OOK transmission schemes are shown in Fig. 7. At a transmission speed of 1 Mb/s or above; error-free transmission was not achieved due to the noise level at receiver, which is responsible for a BER floor of $\sim 3 \times 10^{-4}$. As a result, for real-world applications it is necessary to introduce a BER limit for forward error correction (FEC) at 3.8×10^{-3} , at the cost of 7% overhead [3], as is a common practice in high speed VLC systems [3]. The 7% FEC limit is indicated by the dashed line in the Fig. 7. When power pre-emphasis is not employed the system BER increases drastically with the transmission data rate (or signal's bandwidth) due to the low level of SNR for sub-carriers with higher frequencies. At 7% FEC threshold level, the achievable data rate is around 4 Mb/s, demonstrating the advantage of OFDM over unequalized OOK, where a transmission speed above 2.5 Mb/s cannot be supported.

Finally, when the above mentioned power pre-emphasis technique is applied a transmission speed up to 10 Mb/s can be achieved, which is 2.5 and 4 times faster than the standard OFDM and unequalized OOK schemes, respectively.

In conclusion, we have discussed a 10 Mb/s OFDM VLC link using a new designed PLED with a bandwidth of ~ 350 kHz. A net data-rate/bandwidth of around 30 was achieved by applying a relatively simple but efficient power pre-emphasis technique. Taking into account the robustness of OFDM signal against the frequency-selective and multipath fading channels, this work presents a significant step for the future of PLED-VLC systems as the achieved data rate is sufficient for an indoor Ethernet connection.

The authors gratefully acknowledge Aston University for financial support, Dr Chin-Pang Liu, Prof. Izzat Darwazeh and Dr Haymen Shams, all of University College London for providing the test and measurement equipment.

References

- [1] Z. G. P. A. Haigh, S. Rajbhandari, I. Papakonstantinou, and W. Popoola, "Visible Light Communications: 170 Mb/s using an Artificial Neural Network Equalizer in a Low Bandwidth White Light Configuration," *Journal of Lightwave Technology*, vol. [Submitted], 2013.
- [2] W. Fang-Ming, L. Chun-Ting, W. Chia-Chien, C. Cheng-Wei, H. Hour-Tzu, and H. Chun-Hung, "1.1-Gb/s White-LED-Based Visible Light Communication Employing Carrier-Less Amplitude and Phase Modulation," *Photonics Technology Letters, IEEE*, vol. 24, pp. 1730-1732, 2012.
- [3] G. Cossu, A. M. Khalid, P. Choudhury, R. Corsini, and E. Ciarabella, "3.4 Gbit/s visible optical wireless transmission based on RGB LED," *Optics Express*, vol. 20, pp. B501-B506, 2012/12/10 2012.
- [4] P. A. Haigh, F. Bausi, Z. Ghassemlooy, I. Papakonstantinou, H. Le Minh, C. Flechon, and F. Cacialli, "Visible Light Communications: Real Time 10 Mb/s Link with a Low Bandwidth Polymer Light-Emitting Diode," *Optics Express*, vol. [In Press], 2014.
- [5] P. A. Haigh, Z. Ghassemlooy, I. Papakonstantinou, and M. Hoa Le, "2.7 Mb/s With a 93-kHz White Organic Light Emitting Diode and Real Time ANN Equalizer," *Photonics Technology Letters, IEEE*, vol. 25, pp. 1687-1690, 2013.
- [6] A. M. Khalid, G. Cossu, R. Corsini, P. Choudhury, and E. Ciarabella, "1-Gb/s Transmission Over a Phosphorescent White LED by Using Rate-Adaptive Discrete Multitone Modulation," *Photonics Journal, IEEE*, vol. 4, pp. 1465-1473, 2012.
- [7] J. Vucic, C. Kottke, S. Nerreter, K. D. Langer, and J. W. Walewski, "513 Mbit/s Visible Light Communications Link Based on DMT-Modulation of a White LED," *Lightwave Technology, Journal of*, vol. 28, pp. 3512-3518, 2010.
- [8] P. A. Haigh, Z. Ghassemlooy, and I. Papakonstantinou, "1.4-Mb/s White Organic LED Transmission System Using Discrete Multitone Modulation," *Photonics Technology Letters, IEEE*, vol. 25, pp. 615-618, 2013.
- [9] T. M. Brown and F. Cacialli, "Contact optimization in polymer light-emitting diodes," *Journal of Polymer Science Part B: Polymer Physics*, vol. 41, pp. 2649-2664, 2003 2003.
- [10] Z. E. Lampert, S. E. Lappi, J. M. Papanikolas, C. L. R. Jr, and M. O. Aboelfotoh, "Morphology and chain aggregation dependence of optical gain in thermally annealed films of the conjugated polymer poly[2-methoxy-5-(2'-ethylhexyloxy)-p-phenylene vinylene]," *Journal of Applied Physics*, vol. 113, 2013/06/19/ 2013.
- [11] J. M. Kahn and J. R. Barry, "Wireless infrared communications," *Proceedings of the IEEE*, vol. 85, pp. 265-298, 1997.